MLT OASIS 324 INVERTER/CHARGER

Product Description

- **it is used for home or farm owners faced with unreliable or no grid electricity supply.**
- **The Inverter operates at low-voltage DC and is transformer-based, which translates to a robust and safe product that guarantees trusted owner in the harshest environments**
- **Designed for harsh environments**
- **3,4 and 6kVA**
- **1 Phase transformer-based**
- **Low-Voltage DC (24, 36 & 48V)**

3 YEAR WARRANTY

Specifications

Rates Voltage / Frequency	1 Phase / 230V / 50 Hz
Rated Output Power	3 kVA / 3kW
Rated Output Current	13 A (40 A with AC source)
AC Input	
Input Voltage Range	185 – 250V
Input Frequency Range	42 – 65 Hz
Rated Input Current	40 A
DC Specs	
Battery Voltage (Nominal)	24V
Charging Voltage	28.2 / 29.4V
Battery Technology	Lead Acid / Li-Ion
Efficiency	
Efficiency	Up to 94%
No Load Power Consumption (on)	< 30 W
No Load Power Consumption (Load Sense)	5 W
Dimensions (W x H x D)	352mm x 583mm x 214mm 442mm x 664mm x 302mm (Boxed
Weight	40Kg
Max Ambient for Rated Power	40 Deg